

## Implementation Of The Lanczos Eigen-Solver For The CSI Code

On High Performance Computers

by

Duc T. Nguyen  
Associate Professor  
Department of Civil Engineering  
Old Dominion University  
Norfolk, VA 23529-0241

## EXTENDED ABSTRACT

Lanczos algorithm for the solution of generalized eigenvalue problems have been receiving a lot of attention in recent years [1 - 7] due to its computational efficiency.

The basic steps involved in the Lanczos algorithm are summarized in Table 1 [6]. In Table 1,  $M$  is the structural mass matrix, and  $K_\sigma$  is defined as

$$K_\sigma = K - \sigma M$$

where  $\sigma$  is the shift factor and  $K$  is the structural stiffness matrix.

The focus of this research work is to implement a Lanczos algorithm for the Control-Structure Interaction (CSI) code which can exploit both parallel and vector capabilities provided by modern, high performance computers (such as the Alliant, and Cray-YMP). A partial restoring orthogonality scheme is also developed and incorporated into the basic Lanczos algorithm.

From Table 1, major computational time in the Lanczos algorithm can be identified as:

- I. Matrix-vector multiplication (see steps 1b, 1d, and 2e)
- II. Matrix factorization (see step 2a)
- III. Forward/Backward elimination (see step 2a)

Step 2a (in Table 1) involves the solution for system of simultaneous linear equations. It should be emphasized here that factorization of the matrix  $K_\sigma$  need be done only once. The forward/backward elimination phase, however, needs to be done repeatedly.

The solution for system of simultaneous linear equations in step 2a can be obtained very effectively by incorporating the newly developed Parallel Vector equation SOLVER [8], PVSOLVE, into the Lanczos procedure. Furthermore, to be consistent with the data structure for PVSOLVE, the structural mass matrix  $M$  also needs to be stored in a row-oriented, variable-band fashion. Effective (mass) matrix-vector multiplication which exploits

both parallel and vector speed has also been developed.

The numerical performance (in terms of accuracy and efficiency) of the proposed parallel-vector Lanczos algorithm is demonstrated by solving for the frequencies and modeshapes of the Phase Zero CSI model [9, 10] as shown in Figure 1 on the Alliant and Cray-YMP multi-processor high performance computers. The superior performance of the Lanczos algorithm is illustrated in Table 2.

## References

1. C. Lanczos, "An Iteration Method for the Solution of the Eigenvalue Problem of Linear Differential and Integral Operator," *Journal of Research of the National Bureau of Standards*, 45 (1950), 255-281.
2. G. Golub, R. Underwood, and J.H. Wilkinson, "The Lanczos Algorithm for the Symmetric  $Ax=\lambda Bx$  Problem," Tech. Rep. STAN-CS-72-720, Computer Science Department, Stanford University, 1972.
3. B.N. Parlett and D. Scott, "The Lanczos Algorithm with Selective Orthogonalization," *Mathematics of Computations*, 33, No. 145 (1979), 217-238.
4. B. Nour-Omid, B.N. Parlett, and R.L. Taylor, "Lanczos versus Subspace Iteration for Solution of Eigenvalue Problems," *International Journal for Numerical Methods in Engineering*, 19 (1983), 859-871.
5. B. Nour-Omid and R.W. Clough, "Dynamic Analysis of Structures Using Lanczos Coordinates," *Earthquake Engineering and Structural Dynamics*, 12 (1984), 565-577.
6. T.J.R. Hughes, *The Finite Element Method: Linear Static and Dynamic Finite Element Analysis*, Prentice-Hall, Inc. (1987).
7. O.O. Storaasli, S.W. Bostic, M. Patrick, U. Mahajan, and S. Ma, "Three Parallel Computation Methods for Structural Vibration Analysis," *Proceedings of the AIAA/ASME/ASCE/AHS 29th Structures, Structural Dynamics and Materials Conference*, Williamsburg, VA, April 18-20, 1988, pp. 1401-1411, AIAA Paper No. 88-2391.
8. T.K. Agarwal, O.O. Storaasli, and D.T. Nguyen, "A Parallel-Vector Algorithm for Rapid Structural Analysis on High-Performance Computers," *Proceedings of the AIAA/ASME/ASCE/AHS 31st Structures, Structural Dynamics and Material Conference*, Long Beach, CA, April 2-4, 1990, AIAA Paper No. 90-1149. Also appeared in NASA Technical Memorandum 102614 (For early Domestic Dissemination only), April 1990.
9. W.K. Belvin, K.E. Elliott, A. Bruner, J. Sulla, and J. Bailey, "The LaRC CSI Phase-0 Evolutionary Model Testbed: Design and Experimental Results," Presented at the 4th Annual NASA/DOD Conference on Control/Structures Interaction Technology, November 5-7, 1990, Orlando, Florida.
10. P.G. Maghami, S.M. Joshi, and S. Gupta, "Integrated Control-Structure Design for a Class of Flexible Spacecraft," Presented at the 4th NASA/DOD CSI Technology Conference, November 5-7, 1990, Orlando, Florida.

TABLE 1: The Lanczos Algorithm  
Given an Arbitrary vector  $r_0$  then:

1. Set
  - a.  $q_0 = 0$
  - b.  $\beta_1 = (r_0^T M r_0)^{1/2}$
  - c.  $q_1 = \frac{r_0}{\beta_1}$
  - d.  $p_1 = M q_1$
2. For  $j = 1, 2, \dots$ , repeat:
  - a.  $\bar{r}_j = K_o^{-1} p_j$
  - b.  $\hat{r}_j = \bar{r}_j - q_{j-1} \beta_1$
  - c.  $\alpha_j = q_j^T M \hat{r}_j = p_j^T \hat{r}_j$
  - d.  $r_j = \hat{r}_j - q_j \alpha_j$
  - e.  $\bar{p}_j = M r_j$
  - f.  $\beta_{j+1} = (r_j^T M r_j)^{1/2} = (\bar{p}_j^T r_j)^{1/2}$
  - g. if enough vectors, then terminate the loop
  - h.  $q_{j+1} = \frac{1}{\beta_{j+1}} r_j$
  - i.  $p_{j+1} = \frac{1}{\beta_{j+1}} \bar{p}_j$

Figure 1: Phase Zero CSI Finite Element Model




TABLE 2: Alliant CPU Time Comparison of Subspace and Lanczos algorithms for the Phase Zero CSI Model

No. of Requested Eigen-pairs	Subspace Elapsed Time (Use PVSOLVE) on ALLIANT	Lanczos Elapsed Time (Use PVSOLVE) on ALLIANT
10	50.3 <sup>sec</sup>	38.3 <sup>sec</sup>
15	68.3	41.3
20	79.2	46.9
50	421.2	89.1
100	2083.9	209.5
	$\lambda_{100} = 193.878334$	$\lambda_{100} = 193.875783$